

MAGPRO-REP


Firmware Upgrade Instructions

For the MAGPRO-REP to be supported by the MAGPRO9601 then you will require to update the MAGPRO-REP to Firmware Version 1.7.2, by following the below guide

To start a firmware update from a computer you should first to have a copy of an image update file (with *.bin extension) saved on your computer. For firmware updates use the USB_UTG connector on the main PCB:

1. Connect the panel to the computer using USB cable: Normal A to Micro B type.
2. Enter access code for level 2 or 3 and choose menu 6) SOFT. VERSION.
3. Wait for the message from Windows Explorer for found new Removable Disk.
 - 3.1. Copy image file to Removable Disk
 - 3.2. Eject Removable Disk
 - 3.3. > Panel is configured
4. Use the Windows Explorer file manager to copy the new image update file (with *.bin extension) in
5. Removable Disk directory.
6. When the copying of the image file completes, remove the Removable Disk, as select Eject option from its dialogue box (right click with the mouse over it).
7. If the data in the image file are correct, the panel starts the firmware update procedure of the main microprocessor accompanied with short beeps.
8. Disconnect the USB cable.
9. The panel will reset itself automatically after a successful firmware update.

The latest product manuals and software is available online;
https://www.espuk.com/technical_support/



Elite Security Products UK, Unit 7 Target Park, Shawbank Road, Lakeside, Redditch, Worcestershire, B98 8YN

Tel: +44(0) 1527 51 51 50

Fax: +44(0) 1527 15 01 43

Email: info@espuk.com

Registered in England; Company Registration Number: 02769392; VAT Registration: GB614686525

● ● ● ● ● **ScolmoreGROUP**

For more product information please visit www.espuk.com
E&OE - Errors and Omissions Excepted. B24