

SHDV4R/SHDV8R


Firmware Upgrade Instructions

ESP recommends installing the latest firmware on all **SHDV4R/SHDV8R** systems to comply with **UK PSTI Standards**. This guide provides instructions for updating these products to **Firmware Version 2.10.6**, by following this guide below:

Before beginning the firmware update for your **DVR**, ensure you have the following:

- A Computer
 - The firmware file (**QV-UVR-7J08SH_ZX_V2.10.6.R.20200824...upf**) *saved on your Computer*.
 - A USB stick to transfer the firmware to the DVR.
1. Firstly, extract the firmware file from the .zip file provided in this guide. Ensure that you have chosen the correct firmware for your system; if you have a 4CH system, make sure to select and download the 4CH Firmware.
 2. After inserting the USB stick into the computer, wait for Windows Explorer to display a message indicating that a new Removable Disk has been detected.
 - a. Copy the firmware file (*.upf) to the USB stick.
 - b. Wait until the transfer is complete.
 - c. **Right-click** on the USB stick and select "Eject" from the menu.
 3. Make sure the **USB Stick** has been inserted into the **DVR**.
 4. Please ensure the **DVR** is connected to a monitor or TV screen. Then, right-click on the screen and select "**Main Menu**".
 5. On the **Main Menu** page, click on "**Maintain**" located at the bottom of the screen.
 6. Next, select "**System**" from the menu on the left-hand side of the screen.
 7. After that, click on the "**Upgrade**" tab at the top of the screen.
 8. Once the Upgrade tab is displayed, click "**Detect**" to show the USB stick directory on the screen.
 9. Navigate through the **USB Stick Directory** and locate the firmware file (***.upf firmware file**).
 10. Once you've located the firmware file, left-click on it and then click "**Upgrade**" on the **DVR**.
 11. Please note that the **DVR** will reboot. Once it has restarted, the firmware will be applied.
 12. Once the **DVR** has rebooted, it will prompt you to create a secure password for your CCTV system.
 13. It is also crucial to perform a System Restore on the device; please follow the below to perform a System Restore.
 - a. Navigate into the **Main Menu** page, click on "**Maintain**" located at the bottom of the screen.
 - b. Click "**Config**" on the left-hand side of the screen, then click "**Default**" at the top of the screen.
 - c. On the screen, click "**Select All**" then click "**Restore Factory Settings**".
 - d. The DVR will reboot again, it will once again prompt you to create a secure password for your CCTV system.

The Latest Product Manuals And Software Is Available Online:



Elite Security Products UK, Unit 7 Target Park, Shawbank Road, Lakeside, Redditch, Worcestershire, B98 8YN

Tel: +44(0) 1527 51 51 50

Email: info@espuk.com

Registered in England; Company Registration Number: 02769392; VAT Registration: GB614686525

● ● ● ● ● **ScolmoreGROUP**

For more product information please visit www.espuk.com
E&OE - Errors and Omissions Excepted. B24